



## PRODUCT DISPOSAL INFORMATION

**Product:** DrawingBoard VI and related transducers

**Purpose:** To provide information and guide the recycling process of our products as required by the EU WEEE Directive 2002/96/EC. This document identifies components and materials under the WEEE directive and contains the proper method for disassembling this product.

**Product Disassembly Instructions:** Disassembly instructions provide the steps necessary to be able to separate each part and component. Disassembly instructions also describe the necessary tools to take apart the product.

**Product Material Information:** The following parts, components and substances should be disposed of or recovered separately from other WEEE in compliance with the EU Directive 2002/96/EC.

**Batteries:** Cordless transducers contain batteries:

**Cordless Cursor:** Contains alkaline batteries (2 AA cells)

**Cordless Pen:** Contains silver oxide batteries (2 button cells)

**NOTE:** This product does not use internal batteries based on mercury, cadmium, lead or their compounds.

**Mercury:** Parts used in GTCO CalComp by Turning Technologies products do not contain intentionally added mercury.

**Liquid Crystal Displays (LCD > 100 cm<sup>2</sup>):** Product does not contain an LCD.

**Cathode Ray Tubes (CRT):** Product does not contain a CRT.

**Plastics:** This product may contain plastic parts greater than 25 grams. Many of the parts are bromine free, however they are labeled (molded directly into the plastic) per ISO 11469:2000 (E). Typical marking format is : > Polymer Abbreviation – FR (#) < For example: > PC + ABS FR(40) <

**Capacitors with PCBs:** GTCO CalComp by Turning Technologies does not use capacitors containing PCBs.



**Electrolyte Capacitors (height or diameter > 25 mm):** Electrolyte Capacitors (height or diameter > 25 mm) are not present in this product.

**Asbestos and its compounds:** Parts used in GTCO CalComp by Turning Technologies products do not contain asbestos and its compounds.

**Radioactive Substances:** Parts used in GTCO CalComp by Turning Technologies products do not contain radio-active substances.

**Beryllium and its components:** Beryllium may be present in electronic components as a copper beryllium alloy, which contains less than 2% beryllium. CuBe alloys may be used in various components such as connectors, switches, relays, current carrying springs, integrated circuit sockets and RF shielding.

**Gases:** Parts used in GTCO CalComp by Turning Technologies products do not contain gasses which fall under Regulation (ED 2037/2000) and all hydrocarbons.

**Components with Pressurized Gas:** Product does not contain parts with pressurized gas.

**Liquids:** Product does not contain liquid.

## **Product Disassembly Instructions:**

### ***Corded 16-Button Cursor***

1. Begin by removing the clear plastic backing from the rest of the housing. (Snaps Off)
2. Use screwdriver to remove the four screws holding down the Printed Wiring Board (PWB).
3. Once the PWB has been removed, take out the keypad as well as the 16 plastic keys.
4. Separate the cable from the PWB by removing the cable connector from the pins on the PWB.
5. Remove the wear pad off the clear plastic backing.
6. Remove the coil assembly from the backing by snapping it out of the hole.

### ***Digitizer***

1. Unscrew the Controller cover on the back of the tablet.
2. Remove Grid tails and LED cable from the controller board.
3. Unscrew the corner pieces of the frame.
4. Remove extrusions by taking out the pop-rivets.
5. Remove the grounding strips.
6. Remove Grid Tail and LED cable from the hole in the pan.